

PART NUMBER	DESCRIPTION		
R1,2,8,10,22,23	510 K	1/2 W COMP.	5 %
R3,4	1470 Ω	1/2 W	5 %
R5,6	100 K	1/2 W	5 %
R7,8	500 K	POT.	SP 95
R9	180 K	1/2 W COMP.	10 %
R11	10 K	1/2 W COMP.	10 %
R12	100 Ω	1/2 W	5 %
R13	2150 Ω	1/2 W	5 %
R15			
R16	178 K	1/2 W	5 %
R17,19	1MEG	1/2 W	5 %
R18	17.8 K	1 W	5 %
R20,24,25	33.2 K	1/2 W	2 %
R21,27,43	28.7 K	1/2 W	5 %
R26,28	5 K	POT	SP 94
R29,30	23 K	10 W	5 %
R31,36	2200	1/2 W COMP.	10 %
R32,34	5.0 Ω	3 W. WIRE	5 %
R33	3530 Ω	1/2 W	5 %
R35	700 Ω	3 W WIRE	5 %
R37,38,39,42	3200 Ω	20 W	5 %
R40	5000 Ω	20 W	5 %
R41	12.1 K	1/2 W	5 %
C1,2,3,4,5,6,8,9	0.10 MFD.	600V	MYLAR
C7	30 MFD.	25V	ELECTRO
C12, C5	250 MMFD	10%	CERAMIC
C14	0.22 MFD.	400V	MYLAR
C10,11	250 MMFD	CERAMIC	
C13	30-30 MFD.	200V	ELECTRO
C15,16	140 MFD.	350 V	ELECTRO
C16 A,B,C	40-40-10MFD	475 VDC	
C17	0.01 MFD.	600V. DISC	CERAMIC
D1-9	IN1696, 500PIV.	RECTIFIER	
F1	5 A.	MDX	FUSE
F2	3/4 A	MDL	FUSE
V1	12AY7		
V2	EF 86 / 6267		
V3,4	6SN7GTB		
V5,6	6550 A		
T1	OUTPUT	XFMR	SP 91
T2	MAIN	XFMR	SP 93
L1	FILTER	CHOKE	SP 92

LET	CHANGE	DATE	BY
A	SEE E.C.O. A-1325	7-20-61	
B	SEE E.C.O. H-1335	8-20-62	
C	SEE E.C.O. L-1358	11-1-63	
D	SEE E.C.O. A-1378, A-1379	1-30-64	
E	ADDED DIODE TO BIAS	9-17-64	
F	DRAWING NO. NAS. EE247	12/2/65	RKB

E 081-0247

6. OUTPUT TUBES ARE BALANCED WHEN "BAL POT" R_{26} IS ADJUSTED SO ZERO VOLTAGE IS MEASURED BETWEEN PIN JACKS "A" & "B" AT NO SIGNAL CONDITION.

5. BIAS POT, R_{28}, IS SET FOR A V_5 & V_6 CATHODE CURRENT OF 60 MA. WHEN APPROX. 0.30 VDC IS MEASURED TO GROUND FROM PIN JACK "A" & "B" AT NO SIGNAL CONDITION.

4. MAXIMUM AUDIO POWER OUTPUT AT A LINE VOLTAGE OF 115 VAC IS APPROX. 70 WATTS BEFORE CLIPPING OCCURS.

3. 115 VAC LINE POWER IS APPROX. 120 WATTS AT NO SIGNAL & 220 WATTS AT FULL SIGNAL.

2. DC VOLTAGES SHOWN AS (12) & AC VOLTAGES AS (24) BOTH MEASURED WITH RESPECT TO CHASSIS GROUND. DC VOLTAGES WERE MEASURED WITH A VOM HAVING A SENSITIVITY OF 20 KΩ/VOLT. AC VOLTAGES WERE MEASURED WITH AN AC VTVM HAVING AN INPUT IMPEDANCE OF 2 MEG OHMS.

1. ALL POWER SUPPLY VOLTAGES ARE MEASURED AT NO-SIGNAL CONDITION. ALL AMPLIFIER VOLTAGES V_1 THRU V_6 ARE MEASURED DURING A LOAD CONDITION OF 31 VOLTS ACROSS A 16 Ω RESISTIVE LOAD CONNECTED TO THE 16 Ω OUTPUT TAP.

NOTES:

081-0247

ALLEN ORGAN CO., INC.
MACUNGIE, PENNA.

SCHEMATIC: AMPLIFIER
MODEL 75

081-0247